



REC'D PCT/PTO JUN 2004
INVESTOR IN PEOPLE

**PRIORITY
DOCUMENT**
SUBMITTED OR TRANSMITTED IN
COMPLIANCE WITH RULE 17.1(a) OR (b)

The Patent Office
Concept House
Cardiff Road
Newport
South Wales
NP10 8QQ

REC'D 07 FEB 2003

WIPO PCT

I, the undersigned, being an officer duly authorised in accordance with Section 74(1) and (4) of the Deregulation & Contracting Out Act 1994, to sign and issue certificates on behalf of the Comptroller-General, hereby certify that annexed hereto is a true copy of the documents as originally filed in connection with the patent application identified therein.


In accordance with the Patents (Companies Re-registration) Rules 1982, if a company named in this certificate and any accompanying documents has re-registered under the Companies Act 1980 with the same name as that with which it was registered immediately before re-registration save for the substitution as, or inclusion as, the last part of the name of the words "public limited company" or their equivalents in Welsh, references to the name of the company in this certificate and any accompanying documents shall be treated as references to the name with which it is so re-registered.

In accordance with the rules, the words "public limited company" may be replaced by p.l.c., plc, P.L.C. or PLC.

Re-registration under the Companies Act does not constitute a new legal entity but merely subjects the company to certain additional company law rules.

BEST AVAILABLE COPY

Signed *Andrew Gorse*
Dated 20 January 2003




The
Patent
Office

1/77

Request for grant of a patent

(See the notes on the back of this form. You can also see an explanatory leaflet from the Patent Office to help you fill in this form.)



The Patent Office

Cardiff Road
Newport
Gwent NP9 1RH

Fee: £0

04 JAN 2002

1. Your reference	PADL/JCH/43880		
2. Patent application number (The Patent Office will fill in this part)	0200175.8		
3. Full name, address and postcode of the or of each applicant (underline all surnames)	Marconi Communications Limited PO Box 53 New Century Park Coventry CV3 1HJ		
Patents ADP number (if you know it)			
If the applicant is a corporate body, give the country/state of incorporation	England and Wales	75 192 00001	
4. Title of the invention	DISPERSION COMPENSATION IN OPTICAL COMMUNICATIONS SYSTEMS		
5. Full name, address and postcode in the United Kingdom to which all correspondence relating to this form and translation should be sent	Reddie & Grose 16 Theobalds Road LONDON WC1X 8PL 91001 ✓		
Patents ADP number (if you know it)	COLIN FRANCIS HOSE MARCONI INTELLECTUAL PROPERTY MANAGEMENT THE WILKINS GREAT BADDOW ESSEX CM2 7QS		
6. If you are declaring priority from one or more earlier patent applications, give the country and the date of filing of the or of each of these earlier applications and (if you know it) the or each application number	Country	Priority application (If you know it)	Date of filing (day/month/year)
7. If this application is divided or otherwise derived from an earlier UK application, give the number and the filing date of the earlier application	Number of earlier application	Date of filing (day/month/year)	
8. Is a statement of inventorship and of right to grant of a patent required in support of this request? (Answer 'Yes' if: a) any applicant named in part 3 is not an inventor, or b) there is an inventor who is not named as an applicant, or c) any named applicant is a corporate body. See note (d))	YES		

Patents Form 1/77

9. Enter the number of sheets for any of the following items you are filing with this form. Do not count copies of the same document.

Continuation sheets of this form

Description	7
Claim(s)	3
Abstract	1
Drawing(s)	2

10. If you are also filing any of the following, state how many against each item.

Priority documents

Translations of priority documents

Statement of inventorship and right to grant of a patent (*Patents Form 7/77*)

Request for preliminary examination and search (*Patents Form 9/77*) 1

Request for substantive examination (*Patents Form 10/77*) 1

Any other documents
(please specify)

11. I/We request the grant of a patent on the basis of this application.

Signature

Paddie + Rose

Date

4 January 2002

12. Name and daytime telephone number of person to contact in the United Kingdom

P A D LLOYD
020-7242 0901

Warning

After an application for a patent has been filed, the Comptroller of the Patent Office will consider whether publication or communication of the invention should be prohibited or restricted under Section 22 of the Patents Act 1977. You will be informed if it is necessary to prohibit or restrict your invention in this way. Furthermore, if you live in the United Kingdom, Section 23 of the Patents Act 1977 stops you from applying for a patent abroad without first getting written permission from the Patent Office unless an application has been filed at least 6 weeks beforehand in the United Kingdom for a patent for the same invention and either no direction prohibiting publication or communication has been given, or such direction has been revoked.

Notes

- If you need help to fill in this form or you have any questions, please contact the Patent Office on 0645 500505.
- Write your answers in capital letters using black ink or you may type them.
- If there is not enough space for all the relevant details on any part of this form, please continue on a separate sheet of paper and write "see continuation sheet" in the relevant part(s). Any continuation sheet should be attached to this form.
- If you have answered 'Yes' Patents Form 7/77 will need to be filed.
- Once you have filled in the form you must remember to sign and date it.
- For details of the fee and ways to pay please contact the Patent Office.

DISPERSION COMPENSATION IN
OPTICAL COMMUNICATIONS SYSTEMS

43880

5 This invention relates to apparatus and methods for compensating for dispersion in optical telecommunications systems.

A major requirement of any photonics system is to provide the maximum amount of remotely configurable functionality and flexibility.

10 Dispersion on a high bit rate communications system, both chromatic and polarisation are major problems which usually require some kind of compensation or correction to be applied. Due to the nature of the traffic path distribution around photonic add/drop rings, dispersion
15 compensation has to be done very accurately on a span by span basis so that the accumulated error on a path over multiple spans does not exceed the maximum permissible dispersion. Compensation is therefore specific to a particular fibre route. When this route changes, for example
20 because the system has been reconfigured, the compensation requires modifying. This is difficult to do without knowledge of the new route. This is less of a problem on line networks but in a ring network, traffic can have come from anywhere on the network.

25 Thus, there is a problem in providing accurate dispersion compensation in systems that are remotely configurable. The invention aims to overcome this problem and, in its broadest form, uses a measure of the channel error rate to provide a basis for varying dispersion
30 compensation applied to a signal dropped from the network.

More specifically, there is provided a method of performing dispersion compensation on an optical communications signal, comprising coarsely dispersion compensating the signal as an optical multiplex on a
35 communications network, dropping the signal from the

network, and applying an adjustable dispersion compensation to the dropped signal based on a measure of the error rate in the signal.

5 The invention also provides a method of performing dispersion compensation on an optical communications signal dropped from an optical communications network, comprising splitting the signal multiplex dropped from the network into a plurality of separate signal channels and performing an adjustable dispersion compensation on each channel based on
10 a measure of the error rate in the channel.

The invention further provides apparatus for performing dispersion compensation on an optical communications signal, comprising means for performing coarse dispersion compensation on the signal multiplex on a communications
15 network, means for dropping the signal multiplex from the network, and means for applying an adjustable dispersion compensation to the dropped signal based on a measure of the error rate in the signal.

The invention further provides an add/drop node for an optical communications network, comprising a splitter for
20 dropping a signal multiplex from the network, means for separating the signal multiplex into a plurality of channels, means for measuring the error rate in a channel, and means for applying an adjustable dispersion compensation
25 based on a measure of the error rate.

In an embodiment of the invention, coarse dispersion compensation is applied to the signal multiplex on the network and a fine adjustable compensation is applied to individual channels dropped from the network, in accordance
30 with a measure of signal error rate. This has the advantage that dispersion compensation can be controlled remotely and can be adjusted to take into account the origin of the signal source.

Preferably, a feedback signal is derived from the error
35 rate and used to provide a control signal to set the adjustable dispersion compensation to minimise the error

rate. Preferably, the control signal is dithered to find the compensation setting giving the minimum error rate.

Preferably, the signal is forward error corrected (FEC). A bit error rate signal is derived from a FEC decoder and used to generate the control signal. This has the advantage that changes in error rate caused by dithering the control signal will not be seen by the user at the FEC decoder and corrector will correct the errors before the signal is passed to the user.

An embodiment of the invention will now be described, by way of example only, and with reference to the accompanying drawings in which:

Figure 1 illustrates schematically, a drop node embodying the invention; and

Figure 2 is a flow chart showing a process embodying the invention.

The embodiment to be described uses a combination of coarse and fine compensation to correct for dispersion. Fine compensation uses a measure of the signal error rate to derive a dispersion compensation signal which is applied to the signal after it is dropped from the network before it reaches the user. The embodiment to be described uses forward error correction to derive the error rate and the correction signal although other measures of the error rate are possible. For example, the error rate could be determined directly from the data, if the data format is known, or from the wrapper if present.

A coarse compensation is first applied to the signal on the network. Coarse compensation may be implemented in a known manner using either dispersion compensating fibre (DCF) or a Fibre Bragg grating. DCF fibre has opposite sign dispersion to conventional fibre and the length of the DCF fibre is altered to give the desired amount of dispersion compensation. A fine adjustable dispersion compensation component is then applied at each drop path to perform the final dispersion compensation. As the signal being dropped may be remotely configured to come from a number of

different sources, there may be problems in resetting and maintaining optimisation of the fine dispersion compensator without causing errors to the delivered clients' traffic. The preferred embodiment to be described uses the forward error correction (FEC) bit error rate to overcome this problem.

Referring now to Figure 1, for simplicity, only the drop side of an add/drop node is shown. The construction of the add side is well known to those skilled in the art. Also only the W/E fibre of a two fibre ring is shown. In practice, the network will include an E/W fibre and part of the drop side circuitry will be duplicated to drop signals off both fibres of the network.

The network is a Dense Wavelength Division Multiplex (DWDM) network which carries a plurality of optical channels, typically 32 channels. The signal data in the channels is encoded using a forward error correction algorithm such as the Reed-Solomon algorithm. This enables data errors to be detected and corrected before the data reaches the user, ensuring that the correction process is transparent to the user. The use of FEC introduces a data overhead into the traffic carried on the network but increases ruggedness.

The FEC encoded DWDM signal is carried on the W/E fibre 10 of the ring network and amplified by EDFA amplifier 12. The amplifier stage is not always necessary, depending on the size of the network and the span between network nodes. The multiplexer signal is then passed to a drop coupler 14 which splits the signal into two paths. The through path 18 remains on the network and passes to a channel control unit 16 and the drop path 20 is dropped to be sent to a user, after processing.

The multiplex is band pass filtered by a filter 22 to split out individual channels from the multiplexer. It will be appreciated that only one channel is shown in the figure and that the subsequent processing to be described will be applied to all the dropped channels.

The band pass filter function can be performed in a number of ways, for example, the DWDM signal could be demultiplexed and individual outputs selected, or a 1:n splitter could be used, where n is the number of channels, with a filter on each of the outputs tuned to select individual channels.

The selected output channel is passed to a dispersion compensation unit 24 which applied a dispersion compensation to the selected channel under the control of a control signal 26. The dispersion compensated signal is then passed to a receiver 28 where it is converted into a electrical signal and decoded using a forward error correction (FEC) chip 30. The FEC chip performs two functions. The first is a decode function 32 which decodes the received signal and derives an error signal. The second is a correction function 34 which corrects the decoded signal under the control of the error signal derived by the decoder 32. The decoded and corrected signal is 36 then passed to the user.

The decoder also produces a bit error rate signal BER 38 which is an indication of the number of errors in the received signal. The BER is used as an input to a controller 40 which control the amount of dispersion compensation applied to the signal by the dispersion compensation unit 24.

The dispersion compensation unit operates to minimise the error rate, subject to there being an adequate signal to noise ratio. In order to find the minimum error rate, the controller 40 dithers the dispersion compensation control about an initial estimated set point to find the minimum error rate. Because the FEC chip 30 corrects errors before the signal is passed to the user, the dithering, and the attendant variation in error rate is totally transparent to the user who only sees corrected data.

Figure 2 illustrates how the process operates. A coarse dispersion compensation is set on the network and so the circuit of Figure 1 only performs a fine adjustable dispersion compensation. At step 50, the dispersion

compensation unit 24 is set to an estimated position by the controller 40. At step 52, the bit error rate 38 is retrieved from the FEC decoder 32 and stored. At step 54 a determination is made of whether there are any errors in the signal. If there are not, the bit error rate is necessarily at a minimum and further correction is not necessary. If there are errors, which will usually be the case, the BER is stored at step 56 and the dispersion compensation incremented (or decremented) at step 58. The BER at this position is then retrieved at step 60 and, at step 62 stored compared to the previous BER. If the error rate has decreased, the compensation is being corrected in the correct sense and the compensation is incremented again until the error rate rises again. That point is established as the minimum error rate. If the error rate increases after the first increment, the sense of correction was incorrect and the DCU setting is decremented from its original at step 64. Again, the BER is retrieved at step 66 and, at step 68 compared with the original rate BER_T . If the new rate BER_{T-1} is lower, the DCU is decremented again until the error rate eventually rises, showing that the previous position generated the minimum error rate.

It will be seen that the combination of coarse dispersion compensation on the network and adjustable fine compensation at the drop side of network nodes enables the compensation to be adjusted remotely. This is highly advantageous and enables the compensation to be altered without the network or node having to be taken out of service and without any on site attention. The use of an error measurement is advantageous as it gives an accurate view of the suitability of the dispersion compensation being applied at any given time. Use of a bit error rate derived from a forward error correction decoder is especially advantageous as it allows the dispersion compensation to be fine tuned without the attendant change in error rate affecting the quality of the data output to the user.

Various modifications are possible to the embodiment described without departing from the scope of the invention. For example, fine tuning of the dispersion compensation could be based on a different measure of the error rate in the channel or channels in question.

CLAIMS

1. A method of performing dispersion compensation on an optical communications signal, comprising coarsely dispersion compensating the signal as an optical multiplex on a communications network, dropping the signal from the network, and applying an adjustable dispersion compensation to the dropped signal based on a measure of the error rate in the signal.
2. A method according to claim 1, wherein the adjustable dispersion compensation is applied to individual channels of the signal multiplex dropped from the network.
3. A method according to claim 1, wherein the measure of the signal error rate is used to form a feedback signal to control the adjustable dispersion compensation.
4. A method according to claim 1, 2 or 3, wherein applying the dispersion compensation based on a measure of the error rate comprises adjusting the dispersion compensation to minimise the error rate.
5. A method according to claim 1, 2 or 3, wherein the optical communications signal is forward error correction (FEC) encoded, and wherein the measure of the error rate is a bit error rate derived from a FEC decoder.
6. A method according to claim 4 or 5, comprising dithering the dispersion compensation to determine the dispersion compensation having the minimum error rate.
7. A method of performing dispersion compensation on an optical communications signal dropped from an optical

communications network, comprising splitting the signal multiplex dropped from the network into a plurality of separate signal channels and performing an adjustable dispersion compensation on each channel based on a measure of the error rate in the channel.

5

8. Apparatus for performing dispersion compensation on an optical communications signal, comprising means for performing coarse dispersion compensation on the signal multiplex on a communications network, means for dropping the signal multiplex from the network, and means for applying an adjustable dispersion compensation to the dropped signal based on a measure of the error rate in the signal.

10

9. Apparatus according to claim 8, comprising means for splitting the dropped signal multiplex into a plurality of separate channels, wherein the adjustable dispersion compensation means applies an adjustable compensation to the separated channels.

15

10. Apparatus according to claim 9, comprising means for measuring the error rate in a channel and means for deriving and applying a control signal to adjust the dispersion compensation means from the measured error rate.

20

11. Apparatus according to claim 10, wherein the means for deriving and applying the control signal adjusts the dispersion compensation means to minimise the measured error rate.

25

12. Apparatus according to claims 10 or 11, wherein the signal carried on the network is forward error corrected (FEC) and the means for measuring the error rate comprises an FEC decoder outputting a bit error

30

rate signal to the means for deriving and applying the control signal.

- 5 13. Apparatus according to claim 10, 11 or 12, wherein the means for deriving and applying the control signal comprises means for dithering the control signal to set the dispersion compensation means such that the measured error rate is a minimum.
- 10 14. An add/drop node for an optical communications network, comprising a splitter for dropping a signal multiplex from the network, means for separating the signal multiplex into a plurality of channels, means for measuring the error rate in a channel, and means for applying an adjustable dispersion compensation to the channel based on the error rate.
- 15 15. A method of performing dispersion compensation in an optical communications signal, substantially as herein described with references to Figures 1 and 2 of the accompanying drawings.
- 20 16. Apparatus for performing dispersion compensation in an optical communications signal, substantially as herein described with references to Figures 1 and 2 of the accompanying drawings.
- 25 17. An add/drop node for an optical communications network, substantially as herein described with references to Figures 1 and 2 of the accompanying drawings.

ABSTRACT

**DISPERSION COMPENSATION IN
OPTICAL COMMUNICATIONS SYSTEMS**

(Fig. 1)

5 Dispersion compensation is applied to an optical signal
first by a coarse compensation applied to the signal
multiplex on a communications network and then by a fine
adjustable compensation applied to individual signal
channels dropped from the network. The error rate is
10 measured, for example using forward error correction, and
the dispersion compensation set to minimise the error rate.

1/2




Figure 1

2/2




Figure 2

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☒ **BLACK BORDERS**
- ☐ **IMAGE CUT OFF AT TOP, BOTTOM OR SIDES**
- ☐ **FADED TEXT OR DRAWING**
- ☐ **BLURRED OR ILLEGIBLE TEXT OR DRAWING**
- ☐ **SKEWED/SLANTED IMAGES**
- ☐ **COLOR OR BLACK AND WHITE PHOTOGRAPHS**
- ☐ **GRAY SCALE DOCUMENTS**
- ☐ **LINES OR MARKS ON ORIGINAL DOCUMENT**
- ☐ **REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY**
- ☐ **OTHER:** _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.